

Modeling of static var compensator-high voltage direct current to provide power and improve voltage profile

Abdolmajid Javadian¹, Mahmoud Zadehbagheri², Mohammad Javad Kiani³,
Samad Nejatian⁴, Toile Sutikno⁵

^{1,2,3,4}Department of Electrical Engineering, Yasooj Branch, Islamic Azad University, Yasooj, Iran

⁵Department of Electrical Engineering, Universitas Ahmad Dahlan, Yogyakarta, Indonesia

⁵Embedded System and Power Electronics Research Group, Yogyakarta, Indonesia

Article Info

Article history:

Received Apr 14, 2021

Revised Jun 15, 2021

Accepted Jun 27, 2021

Keywords:

FACTS devices

High voltage direct current

Newton-Raphson method

Power flow

Static var compensator

ABSTRACT

Transmission lines react to an unexpected increase in power, and if these power changes are not controlled, some lines will become overloaded on certain routes. Flexible alternating current transmission system (FACTS) devices can change the voltage range and phase angle and thus control the power flow. This paper presents suitable mathematical modeling of FACTS devices including static var compensator (SVC) as a parallel compensator and high voltage direct current (HVDC) bonding. A comprehensive modeling of SVC and HVDC bonding in the form of simultaneous applications for power flow is also performed, and the effects of compensations are compared. The comprehensive model obtained was implemented on the 5-bus test system in MATLAB software using the Newton-Raphson method, revealed that generators have to produce more power. Also, the addition of these devices stabilizes the voltage and controls active and reactive power in the network.

This is an open access article under the [CC BY-SA](#) license.



Corresponding Author:

Mahmoud Zadehbagheri

Department of Electrical Engineering

Yasooj Branch, Islamic Azad University, yasooj, Iran

Email: Mahmoud.zadehbagheri.2009@gmail.com

NOMENCLATURE

S	: Apparent power	Y	: Line and element admittance
P	: Active power	G	: Line and element conductance
Q	: Reactive power	B	: Line and element susceptance
U, V, E	: Voltages of terminal, effective, bus	J, J_1, J_2, J_3, J_4	: Jacobin matrix and its elements
I	: Line current	x	: State variable in power flow equation
δ, θ	: Phase angles	$f(x)$: State variables function
X	: Line and element reactance	R_{dc}	: Resistance in the connection line of HVDC

1. INTRODUCTION

The use of flexible alternating current transmission system (FACTS) and high-voltage direct current (HVDC) equipments are considered by designers of electrical transmission networks due to the increased demand for transmission networks, the creation of long transmission line routes, long distance of production centers from consumption centers, accumulation of energy resources in specific places and wide distribution of consumption centers [1]–[8]. This equipment can control both active and reactive power simultaneously, regulate voltage range and reduce power flow on overloaded lines by creating the desired voltage level [9]–[12]. Flexible alternating current transmission system devices can increase load capacity, portability and

reliability and improve system line density [13]. Load flow studies are essential for the analysis, design, control, and economic planning of the future of transmission and power systems [11].

The Newton-Raphson power flow method is an effective and practical method due to its quadratic convergence and the fact that the number of iterations is independent of the system size and has a high convergence rate [11], [14]. Power transmission capacity is influenced by factors such as thermal constraints, voltage constraints, and limited stability, which leads to dense lines and reduction of security margins and definitive load [8], [12], [15], [16].

In order to meet the requirements for system control, a set of equipment is used that include tools that control power and voltage [10]. Low portability means the need for more production resources [13]. Therefore, practical measures should be taken to improve portability. FACTS devices are used for increasing portability and power quality [13]. Energy systems can be developed by installing HVDC transmission lines [17]–[20], which resolve the problems of low impedance and unbalanced power flow because they control power based on electronic power devices [13]. A combination of series and parallel controllers with line impedance control and voltage regulator manage the active and reactive power in the system [13]. High-voltage direct current systems are of particular importance due to the accumulation of energy resources in specific locations, wide distribution of consumption centers, the need to connect to adjacent networks, the need for transmission by underground and sea routes and the economic benefits of high-power transmission over long distances [13], [21].

The disadvantages of HVDC lines, on the other hand, include high energy conversion costs and reactive power requirements of converters [17]. Flexible alternating current transmission system controllers used in this paper included static var compensator or static var compensator (SVC) and HVDC link was also used in the transmission line. High-voltage direct current systems are comprised of two converters, one capable of regulating voltage and the other capable of quickly transmitting and controlling active power [9]. Provided that direct current (DC) converters inherently absorb reactive power, a reactive power source such as an SVC can be used near the converter [10]. SVC is used to generate or absorb reactive power in parallel in the network to control the bus voltage [13]. Much research has been carried out on the use of FACTS devices and HVDC lines, included proposing two suitable multi-terminal VSC-HVDC models for load flow study using the Newton-Raphson algorithm [22], Newton-Raphson HVDC power flow modeling [23]–[25], and multi-terminal VSC-HVDC load flow was modeled using the AC/DC load flow algorithm by MATLAB and MATPOWER software programs [26], [27].

In Vinkovic and Mihalic [28], the general method for dual modeling of FACTS devices and their series and parallel modeling were studied. SVC has been used to optimize the Newton-Raphson power flow modeling [29], [30]. In [31], a control method for the coordination of HVDC and FACTS was proposed with the aim of obtaining small signal stability of the power system, which indicated that by changing the parameters, the oscillation between adjacent areas for production was reduced. In [32], a multiple optimal power flow (OPF) solution method was presented with the presence of FACTS devices, which were very powerful and fine-tuned the unequal constraints of the system. The optimal multi-objective placement of FACTS controllers including SVC, thyristor-controlled series compensation (TCSC), and unified power flow controller (UPFC) for power system operational planning has been investigated in [33]–[37]. The optimal power flow of the HVDC two-terminal system was obtained with the help of a genetic algorithm and a backtracking search algorithm in [17], [38]. The integration of an SVC into the distribution generator in the network, led to an improvement in voltage regulation and a reduction in distribution network losses [39]. For optimal reactive power and coordination between FACTS devices such as SVC and TCSC with other sources, simple particle swarm optimization (SPSO), evolutionary particle swarm optimization (ESPO), and adaptive particle swarm optimization (APSO) algorithms were used [40]–[51]. Power flow modeling of the AC-DC hybrid HVDC multi-terminal system was presented in [52], [53], which achieved a very good power flow and convergence solution. In [54], a new power flow method including FACTS and HVDC devices was investigated in which the bus equations included a P-Q bus (in this bus the real power (P) and reactive power (Q) are specified) in the alternating current (AC) system to remove components from the AC system and increase the convergence speed. In none of the previous works the simultaneous use of FACTS devices has been investigated using comprehensive modeling. In this article, the simultaneous combination of two devices and between two buses has been used, but in previous works, either these devices have been used individually or not simultaneously between two buses to investigate its effects. We sought to investigate the modeling of SVC and HVDC devices and to obtain comprehensive modeling of the simultaneous application of all the two devices by the Newton-Raphson power flow method and determine the effects of series and parallel compensations on the network. Simulations were implemented with the help of MATLAB software on a 5-bus test system.

2. RESEARCH METHOD

2.1. Modeling of FACTS devices

The general model of FACTS devices when used in series on the network as Figure 1 is formulated in the manner [28].

$$S_{ST} = P_{ST} + jQ_{ST} = U_S(-I_S^*) \quad (1)$$

$$S_{RT} = P_{RT} + jQ_{RT} = U_R(-I_S^*) \quad (2)$$

$$P_T = P_{ST} + P_{RT} \quad (3)$$

The model of the parallel application of FACTS devices is as Figure 2 [28].

$$S_{PT} = P_{PT} + jQ_{PT} = U_P(-I_P^*) \quad (4)$$

$$P_{PT} = -U_P(\text{Re}[I_P] \cos \delta_P + \text{Im}[I_P] \sin \delta_P) \quad (5)$$

$$Q_{PT} = -U_P(\text{Re}[I_P] \sin \delta_P - \text{Im}[I_P] \cos \delta_P) \quad (6)$$

In these equations, S, P, Q and I are the apparent power, active and reactive powers, and line current, respectively. Power control by FACTS devices according to the power as shown in (7) [34].

$$P = \frac{V_i V_j}{X_{ij}} \sin(\theta_i - \theta_j) \quad (7)$$

$$V_i V_j \implies SVC \quad \sin(\theta_i - \theta_j), V_i V_j, X_{ij} \implies UPFC$$

$$X_{ij} \implies TCSC$$

2.2. SVC modeling

In this paper, SVC is modeled as an ideal reactive power source injected into bus A. Static VAR compensator can continuously generate reactive power compensation by operating in inductive and capacitive modes. Static VAR compensator model and structure are specified in Figure 3 [55]. The role of SVC is to keep the voltage in the bus constant, which is done by injecting power into the bus [30]. In modeling, we considered SVC as a parallel variable susceptance as Figure 3 [9], [30], [55].

$$I_{SVC} = jB_{SVC}V_a \quad (8)$$

The power absorbed or injected into the bass is as (9) [30][55].

$$Q_{SVC} = Q_a = -V_a^2 B_{SVC} \quad (9)$$




Figure 1. Model of a FACTS series branch [28]




Figure 2. Model of a FACTS parallel branch [28]




Figure 3. Model of parallel variable susceptance for SVC

2.3. HVDC system modeling

A HVDC system consists of two voltage source converters connected to busbars A and B by transformers. The equivalent circuit of the HVDC system includes a combination of the voltage source and transformer impedance series. Depending on their application, both converters are connected back to back or by a DC cable [21], [24]. The HVDC system is conveniently modeled with two voltage sources along with an equation that states the active power condition. With the introduction of HVDC, the range of transmission power increased (from below 1000 W to 3 to 4 GW) [56]. High-voltage alternative current (HVAC) design

and construction are not economical for long distances, but using HVDC improves the cost and transmission of high voltages [57]. In the system HVDC and FACTS devices, due to less insulation and resistance DC less than AC, fewer losses[58], the need for two conductors in the system and as a result of the volume and space of the less to install, reduce of the thickness and cross-section of the cable in a certain power, use of the ground as a return wire, it has lower costs than HVAC, which in Figure 4, we see the difference in costs based on references [59], [60]. Moreover, the HVDC is able to improve stability of inter-connected HVAC by modulating power in response to small/large disturbances [61]. The DC terminals will always be more expensive than AC terminals simply because they have to have the components to transform DC voltage as well as convert the DC to AC. But the DC voltage conversion and circuit breakers have been dropping in price, the break-even price continues to drop. The HVDC model in power flow studies is as Figure 5 [23], [24], [62].




Figure 4. Compare the costs of HVDC and HVAC systems [60]




Figure 5. Model of HVDC for power flow [9]

$$E_1 = V_1(\cos \delta_1 + j \sin \delta_1) \quad (10)$$

$$E_2 = V_2(\cos \delta_2 + j \sin \delta_2) \quad (11)$$

$$\begin{bmatrix} I_a \\ I_b \end{bmatrix} = \begin{bmatrix} Y_1 & -Y_1 & 0 & 0 \\ 0 & 0 & Y_2 & -Y_2 \end{bmatrix} \cdot \begin{bmatrix} E_a \\ E_1 \\ E_b \\ E_2 \end{bmatrix} \quad (12)$$

$$P = \text{Re}\{E_1 I_1^*\} \quad (13)$$

$$Q = \text{Im}\{E_1 I_1^*\} \quad (14)$$

For both HVDC components connected by a DC cable [9], [23].

$$\text{Re}\{V_1 I_1^* + V_2 I_2^* + V_{DC} I_{DC}\} = 0 \quad (15)$$

And if $R_{dc} = 0$ (That R_{dc} resistor connection line in HVDC) then: [9], [23].

$$\text{Re}\{V_1 I_1^* + V_2 I_2^*\} = 0 \quad (16)$$

2.4. Comprehensive SVC-HVDC modeling for power flow

Due to the limitations of transmission lines and the advantages of using FACTS devices as parallel and series compensators in the network, also, for connecting the power grid and taking into account the advantages of HVDC lines, establishing HVDC connections as a complement to AC systems is essential. In this paper, a comprehensive model for modeling SVC and HVDC devices was used as Figure 6. Then, the Newton-Raphson power flow on the final model was applied. According to the Figure 6, an SVC is used as a parallel compensator and an HVDC as a link.




Figure 6. Model of SVC-TCSC-HVDC for power flow

By writing the relations of currents passing through buses and lines and the relation of power and separation of their real and imaginary parts,

$$S_i = P_i + jQ_i = E_i I_i^* \quad (17)$$

$$E_i = V_i (\cos \theta_i + j \sin \theta_i) \quad (18)$$

$$E_a = V_a (\cos \theta_a + j \sin \theta_a) \quad (19)$$

$$E_b = V_b (\cos \theta_b + j \sin \theta_b) \quad (20)$$

$$E_1 = V_1 (\cos \delta_1 + j \sin \delta_1) \quad (21)$$

$$E_2 = V_2 (\cos \delta_2 + j \sin \delta_2) \quad (22)$$

$$Y_i = G_i + jB_i \quad (23)$$

$$Y_0 = jB_{SVC} \quad (24)$$

$$Y_1 = G_1 + jB_1 \quad (25)$$

$$Y_2 = G_2 + jB_2 \quad (26)$$

$$Y_3 = Y_0 + Y_1 = G_1 + jB_3 \quad (27)$$

$$B_3 = B_{SVC} + B_1 \quad (28)$$

where:

$$P_a = G_1 V_a^2 - G_1 V_1 V_a \cos(\theta_a - \delta_1) - B_1 V_1 V_a \sin(\theta_a - \delta_1) \quad (29)$$

$$Q_a = -B_3 V_a^2 - G_1 V_1 V_a \sin(\theta_a - \delta_1) + B_1 V_1 V_a \cos(\theta_a - \delta_1) \quad (30)$$

$$P_b = -G_2 V_b^2 + G_2 V_2 V_b \cos(\theta_b - \delta_2) + B_2 V_2 V_b \sin(\theta_b - \delta_2) \quad (31)$$

$$Q_b = B_2 V_b^2 + G_2 V_2 V_b \sin(\theta_b - \delta_2) - B_2 V_2 V_b \cos(\theta_b - \delta_2) \quad (32)$$

$$Q_{SVC} = -V_a^2 B_{SVC} \quad (33)$$

$$P_1 = -G_1 V_1^2 + G_1 V_1 V_a \cos(\theta_a - \delta_1) - B_1 V_1 V_a \sin(\theta_a - \delta_1) \quad (34)$$

$$Q_1 = B_1 V_1^2 - G_1 V_1 V_a \sin(\theta_a - \delta_1) - B_1 V_1 V_a \cos(\theta_a - \delta_1) \quad (35)$$

$$P_2 = -G_2 V_2^2 + G_2 V_2 V_b \cos(\theta_b - \delta_2) - B_2 V_2 V_b \sin(\theta_b - \delta_2) \quad (36)$$

$$Q_2 = B_2 V_2^2 - G_2 V_2 V_b \sin(\theta_b - \delta_2) - B_2 V_2 V_b \cos(\theta_b - \delta_2) \quad (37)$$

where V_a , V_b , V_1 , V_2 , θ_a , θ_b , δ_1 , and δ_2 are the voltage and angles of the bus a , b , and HVDC link, respectively. B_1 , B_2 and B_{SVC} are susceptance for the rectifier, inverter and SVC, respectively. G_1 and G_2 are the side conductance of the rectifier and inverter, respectively. P_1 , P_2 , P_a , P_b are the active powers of rectifier and inverter, buses a , and b , respectively. Finally, Q_a , Q_b , Q_{SVC} , Q_1 , and Q_2 are the reactive powers for a , and b buses, the SVC reactive power and the rectifier and inverter sides of the model, respectively.

In (29) to (37) we see that the hybrid model is effective in active and reactive powers related to buses and lines. For example, in (30) B_3 is used which is a combination of SVC and HVDC. These show a comprehensive hybrid model that can be generalized to larger networks, and this model can also be used in load flow and stability analysis, etc. To solve the Newton-Raphson power flow (38)-(44). The Newton-Raphson method is scientifically efficient due to quadratic convergence and high convergence velocity, which is obtained by extending the Taylor series [63]–[67].

$$[f(x)] = [J] \cdot [x] \quad (38)$$

The matrix $[J]$ is the Jacobin matrix obtained by the partial derivatives of each function as shown in (29)-(37) relative to the variables:

$$x = \begin{bmatrix} \Delta\theta_a \\ \frac{\Delta V_a}{V_a} \\ \frac{\Delta B_{SVC}}{B_{SVC}} \\ \Delta\delta_1 \\ \frac{\Delta V_1}{V_1} \\ \Delta\delta_2 \end{bmatrix}, F(x) = \begin{bmatrix} \Delta P_a \\ \Delta Q_a \\ \Delta Q_{SVC} \\ \Delta P_1 \\ \Delta Q_1 \\ \Delta P_{HVDC} \end{bmatrix}, J = \begin{bmatrix} [J_1] & [J_2] \\ [J_3] & [J_4] \end{bmatrix} \quad (39)$$

$$J_1 = \begin{bmatrix} \frac{\partial P_a}{\partial \theta_a} & \frac{\partial P_a}{\partial V_a} V_a & 0 \\ \frac{\partial Q_a}{\partial \theta_a} & \frac{\partial Q_a}{\partial V_a} V_a & \frac{\partial Q_a}{\partial B_{SVC}} B_{SVC} \\ 0 & 0 & \frac{\partial Q_a}{\partial B_{SVC}} B_{SVC} \end{bmatrix} \quad (40)$$

$$J_2 = \begin{bmatrix} \frac{\partial P_a}{\partial \delta_1} & \frac{\partial P_a}{\partial V_1} V_1 & 0 \\ \frac{\partial Q_a}{\partial \delta_1} & \frac{\partial Q_a}{\partial V_1} V_1 & 0 \\ 0 & 0 & 0 \end{bmatrix} \quad (41)$$

$$J_3 = \begin{bmatrix} \frac{\partial P_1}{\partial \theta_a} & \frac{\partial P_1}{\partial V_a} V_a & 0 \\ \frac{\partial Q_1}{\partial \theta_a} & \frac{\partial Q_1}{\partial V_a} V_a & 0 \\ \frac{\partial P_{HVDC}}{\partial \theta_a} & \frac{\partial P_{HVDC}}{\partial V_a} V_a & 0 \end{bmatrix} \quad (42)$$

$$J_4 = \begin{bmatrix} \frac{\partial P_1}{\partial \delta_1} & \frac{\partial P_1}{\partial V_1} V_1 & 0 \\ \frac{\partial Q_1}{\partial \delta_1} & \frac{\partial Q_1}{\partial V_1} V_1 & 0 \\ \frac{\partial P_{HVDC}}{\partial \delta_1} & \frac{\partial P_{HVDC}}{\partial V_1} V_1 & \frac{\partial P_{HVDC}}{\partial \delta_2} \end{bmatrix} \quad (43)$$

Where in the above relations J , J_1 , J_2 , J_3 , J_4 are the Jacobin matrix and its components and $f(x)$ are the function of state variables and x are state variables in load flow equations and we have:

$$P_{HVDC} = P_1 - P_2 \quad (44)$$

Since the active power is set at the end of the rectifier in the HVDC line and the voltage range at bus b is kept constant, the equations of active and reactive power of the inverter are additional [9].

3. RESULTS AND DISCUSSION

We applied the model obtained in the previous section on a 5-bus test system according to Figure 7, where all the information about the buses and lines and the whole network was extracted from reference [38]. The information required for the test system is provided in Appendix. First, power flow was without adding FACTS devices, and then in this network, we added the SVC and HVDC devices individually to the network and observed the results. Finally, based on the SVC-HVDC model obtained in the previous section of this paper, all the both devices were added to the system and the results were recorded. In this paper, the focus was on load flow in buses on which the devices have a direct effect, such as buses 3 and 4 (Lake and Main), although they affect the whole network.




Figure 7. System test 5 buses with SVC-HVDC

In Figure 8, which shows voltage changes in the presence of various FACTS devices, the voltage state for stabilization at 1 p.u. is presented. Using SVC, was better than the mode without FACTS devices and the mode of using HVDC, and in buses 3 and 4, it was 1 p.u. closer. But the best state and voltage stabilization occurred in the case that the SVC-HVDC combination was used. Also, compared to the different references in Figure 9, the SVC-HVDC model has the best state of recovery and voltage stabilization. The best state for voltage improvement was the mode of using SVC in reference [9].




Figure 8. Voltage of models




Figure 9. Voltage in different model of references

In all diagrams and figures, PG1, PG2, P3-4 and P4-3 are the active powers produced by the North and South generators, and the active powers are between buses 3 and 4, respectively. In addition, QG1, QG2, Q3-4 and Q4-3 are the reactive powers generated by the North and South generators, and the reactive powers are between buses 3 and 4, respectively. By applying Newton-Raphson load flow in the final model and different models in Figure 10 and Figure 11 (by keeping the output of the South generator constant at 40 MW), an increase in active and reactive power between the buses used by the devices is noted, which is the best way to use SVC-HVDC. It is the most efficient model in compensating active and reactive power. In the final hybrid model, the generators are forced to produce more power, which is more costly for the system and is among the disadvantages of the system.




Figure 10. Result of active power flow




Figure 11. Result of reactive power flow

By comparing load flow in the models used in this paper and the different references in Figure 12 and Figure 13, we see a further spike in active and reactive power, which indicates the efficiency of the proposed SVC-HVDC hybrid model in the network. Comparing this model with the references in Figure 12 and Figure 13, it can be concluded that good compensation is obtained for the system. Besides, an increase in active and reactive power between the buses and lines, and at the same time, voltage stabilization in the Main and Lake Buses in this SVC-HVDC model were obtained. However, this paper examined a comprehensive model for the simultaneous effects of all the two types of devices for power flow and controlled the active and reactive power simultaneously, which had not been done in any of the previous studies [9], [23]–[25], [29]–[31], [33], [34], [40], [52], [54], [57], [68]–[70].




Figure 12. Active power flow indifferent model of references




Figure 13. Reactive power flow indifferent model of references

4. CONCLUSION

In this paper, models for the use of different flexible alternating current transmission system (FACTS) devices were presented, and finally a hybrid model including static var compensator (SVC) as a parallel compensator and high voltage direct current (HVDC) link was modeled for simultaneous use in a 5-bus network and Newton-Raphson load flow. According to the results, the installation of several types of FACTS devices simultaneously with SVC-HVDC, by increasing the flexibility of the power network to achieve better results, improved the voltage profile and compensation to increase the active and reactive power in the network. In this model, we observed an increase in the power generation of generators, which increases the production cost in the network and is one of the disadvantages of the model. The results showed that the proposed method had good performance. This study obtained a suitable hybrid model for load flow studies that can be generalized to larger networks and this model can be used in stability discussion studies and other power system studies. Future studies are needed to examine the optimal load flow of this model and optimal placement of these devices in the network.

APPENDIX

The information required for the test system in Figure 6 and the range of selected parameters for the equipment is as:

SVC	BSVC0 = 0.02		
	BLO = -0.2	V0 = 1.00	QSVCO = -100 MVAr 100 MVAr
HVDC	Rdc = 0.00	BHi = 0.2	
		V1' = 1.00	
		V2' = 1.00	
		VLO = 0.9	
		VHi = 1.1	
		PHVDC0 = 0.4 MW 300 MW	

Where BSVC0, BLO, BHi, V0 and QSVCO are the initial values and upper and lower limits of the susceptance, the initial voltage and range of change of reactive power values in SVC, respectively. Also, V1', V2', VLO and VHi are the initial voltage values on the rectifier and inverter side and their change amplitude, respectively. PHVDC0 the range of change of active power values is HVDC. The rest of the information related to buses, lines and generator information is available in reference [38].

REFERENCES

- [1] N. A. M. Kamari, I. Musirin, Z. A. Hamid, and A. A. Ibrahim, "Optimal tuning of SVC-PI controller using whale optimization algorithm for angle stability improvement," *Indones. J. Electr. Eng. Comput. Sci.*, vol. 12, no. 2, pp. 620–624, 2018, doi: 10.11591/ijeecs.v12.i2.pp620-624.
- [2] Z. A. Hamid, I. Musirin, M. A. A. Nan, and Z. Othman, "Optimal voltage stability improvement under contingencies using flower pollination algorithm and thyristor controlled series capacitor," *Indones. J. Electr. Eng. Comput. Sci.*, vol. 12, no. 2, pp. 497–504, 2018, doi: 10.11591/ijeecs.v12.i2.pp497-504.
- [3] N. A. M. Kamari, I. Musirin, M. K. M. Zamani, and S. A. Halim, "Oscillation stability enhancement using multi-objective swarm based technique for SMIB system," *Indones. J. Electr. Eng. Comput. Sci.*, vol. 16, no. 2, pp. 631–639, 2019, doi: 10.11591/ijeecs.v16.i2.pp631-639.
- [4] M. K. M. Zamani, I. Musirin, S. I. Suliman, and M. M. Othman, "Chaotic immune symbiotic organisms search for SVC installation in voltage security control," *Indones. J. Electr. Eng. Comput. Sci.*, vol. 16, no. 2, pp. 623–630, 2019, doi: 10.11591/ijeecs.v16.i2.pp623-630.
- [5] S. Hocine and L. Djamel, "Optimal number and location of UPFC devices to enhance voltage profile and minimizing losses in electrical power systems," *Int. J. Electr. Comput. Eng.*, vol. 9, no. 5, pp. 3981–3992, 2019, doi: 10.11591/ijece.v9i5.pp3981-3992.
- [6] E. Sreeshobha and P. V. N. Prasad, "Economic profit estimation of transmission system using novel contingency ranking with Markov modelling," *Indones. J. Electr. Eng. Comput. Sci.*, vol. 18, no. 2, pp. 565–572, 2020, doi: 10.11591/ijeecs.v18.i2.pp565-572.
- [7] A. N. Alsammak and H. A. Mohammed, "Power quality improvement using fuzzy logic controller based unified power flow controller (UPFC)," *Indones. J. Electr. Eng. Comput. Sci.*, vol. 21, no. 1, pp. 1–9, 2021, doi: 10.11591/ijeecs.v21.i1.pp1-9.
- [8] I. M. Wartana, N. P. Agustini, and S. Sreedharan, "Optimal integration of wind energy with a shunt-FACTS controller for reductions in electrical power loss," *Indones. J. Electr. Eng. Comput. Sci.*, vol. 23, no. 1, 2021, doi: 10.11591/ijeecs.v23.i1.ppab-cd.
- [9] E. Acha, C. R. Fuerte-Esquivel, H. Ambriz-Perez, and C. Angeles-Camacho, *FACTS: modelling and simulation in power networks*. John Wiley & Sons, 2004.
- [10] K. Prabha, N. J. Balu, M. G. Lauby, and P. Kundur, *Power System Stability and Control*. McGraw-Hill Professional, 1994.
- [11] H. Saadat, *Power System Analysis*. McGraw-Hill College, 1998.
- [12] C. H. N. Kumari and K. C. Sekhar, "Power flow control using FACTS device in modern power system," in *2017 IEEE International Conference on Circuits and Systems (ICCS)*, 2017, pp. 372–376.
- [13] L. Gyugyi and N. G. Hingorani, *Understanding FACTS: Concepts and Technology of Flexible AC Transmission Systems*. Wiley-IEEE Press, 1999.
- [14] L. T. Tay, W. O. C. Fen, and L. J. Awal, "Improved Newton-raphson with schur complement methods for load flow analysis," *Indones. J. Electr. Eng. Comput. Sci.*, vol. 16, no. 2, pp. 599–605, 2019, doi: 10.11591/ijeecs.v16.i2.pp699-605.
- [15] M. K. Zarkani, A. S. Tukkee, and M. J. Alali, "Optimal placement of facts devices to reduce power system losses using evolutionary algorithm," *Indones. J. Electr. Eng. Comput. Sci.*, vol. 21, no. 3, pp. 1271–1278, 2021, doi: 10.11591/ijeecs.v21.i3.pp1271-1278.
- [16] N. F. B. Aswan, M. N. Abdullah, and A. H. A. Bakar, "A review of combined economic emission dispatch for optimal power dispatch with renewable energy," *Indones. J. Electr. Eng. Comput. Sci.*, vol. 16, no. 1, pp. 33–40, 2019, doi: 10.11591/ijeecs.v16.i1.pp33-40.
- [17] K. Ayan and U. Kılıç, "Optimal power flow of two-terminal HVDC systems using backtracking search algorithm," *Int. J. Electr. Power Energy Syst.*, vol. 78, pp. 326–335, 2016.
- [18] O. E. Oni, A. G. Swanson, and R. P. Carpanen, "Impact of LCC-HVDC multiterminal on generator rotor angle

- stability," *Int. J. Electr. Comput. Eng.*, vol. 10, no. 1, pp. 22–34, 2020, doi: 10.11591/ijece.v10i1.pp22-34.
- [19] A. A. Daoud, A. F. Abouzeid, and S. S. Dessouky, "Offshore wind power integration to support weak grid voltage for industrial loads using VSC-HVDC transmission system," *Int. J. Electr. Comput. Eng.*, vol. 11, no. 3, pp. 1876–1885, 2021, doi: 10.11591/ijece.v11i3.pp1876-1885.
 - [20] J. A. Varela and M. A. Rios, "Interconnection viability of high demand isolated area through a HVDC-VSC link," *Int. J. Electr. Comput. Eng.*, vol. 11, no. 2, pp. 1002–1010, 2021, doi: 10.11591/ijece.v11i2.pp1002-1010.
 - [21] R. Rudervall, J. P. Charpentier, and R. Sharma, "High voltage direct current (HVDC) transmission systems technology review paper," *Energy week*, vol. 2000, pp. 1–19, 2000.
 - [22] X.-P. Zhang, "Multiterminal voltage-sourced converter-based HVDC models for power flow analysis," *IEEE Trans. Power Syst.*, vol. 19, no. 4, pp. 1877–1884, 2004.
 - [23] E. Acha, B. Kazemtabrizi, and L. M. Castro, "A new VSC-HVDC model for power flows using the Newton-Raphson method," *IEEE Trans. Power Syst.*, vol. 28, no. 3, pp. 2602–2612, 2013.
 - [24] M. A. AboElHassan, S. Kamel, and M. Ebeed, "Simple modeling of HVDC systems into Newton-Raphson load flow algorithm," in *2016 Eighteenth International Middle East Power Systems Conference (MEPCON)*, 2016, pp. 832–836.
 - [25] C. R. Fuerte-Esquivel and E. Acha, "A Newton-type algorithm for the control of power flow in electrical power networks," *IEEE Trans. power Syst.*, vol. 12, no. 4, pp. 1474–1480, 1997.
 - [26] J. Beerten, S. Cole, and R. Belmans, "Generalized steady-state VSC MTDC model for sequential AC/DC power flow algorithms," *IEEE Trans. Power Syst.*, vol. 27, no. 2, pp. 821–829, 2012.
 - [27] J. Beerten, S. Cole, and R. Belmans, "A sequential AC/DC power flow algorithm for networks containing multi-terminal VSC HVDC systems," in *IEEE PES General Meeting*, 2010, pp. 1–7.
 - [28] A. Vinkovic and R. Mihalic, "Universal method for the modeling of the 2nd generation FACTS devices in Newton-Raphson power flow," *Int. J. Electr. Power Energy Syst.*, vol. 33, no. 10, pp. 1631–1637, 2011.
 - [29] R. P. Singh and S. Zope, "Newton-Raphson Power Flow Models Of SVC Optimization by PSO," *IJDACR*, vol. 5, Sep. 2016.
 - [30] F. Rabea, S. Kamel, F. Jurado, and O. Abdel-Rahim, "Implementation of a simplified SVC model into Newton-Raphson load flow algorithm," in *2018 International Conference on Innovative Trends in Computer Engineering (ITCE)*, 2018, pp. 374–379.
 - [31] M. Zadehbagheri, M. Pishavaei, R. Ildarabadi, and T. Sutikno, "The coordinated control of FACTS and HVDC using H-infinity robust method to stabilize the inter-regional oscillations in power systems," *Int. J. Power Electron. Drive Syst.*, vol. 8, no. 3, pp. 1274–1284, 2017, doi: 10.11591/ijpeds.v8i3.pp1274-1284.
 - [32] H. Ambriz-Perez, E. Acha, and C. R. Fuerte-Esquivel, "High voltage direct current modelling in optimal power flows," *Int. J. Electr. Power Energy Syst.*, vol. 30, no. 3, pp. 157–168, 2008.
 - [33] A. L. Ara, A. Kazemi, and S. A. N. Niaki, "Multiobjective optimal location of FACTS shunt-series controllers for power system operation planning," *IEEE Trans. Power Deliv.*, vol. 27, no. 2, pp. 481–490, 2011.
 - [34] I. Khan, M. A. Mallick, M. Rafi, and M. S. Mirza, "Optimal placement of FACTS controller scheme for enhancement of power system security in Indian scenario," *J. Electr. Syst. Inf. Technol.*, vol. 2, no. 2, pp. 161–171, 2015.
 - [35] I. S. Shahbudin *et al.*, "FACTS device installation in transmission system using whale optimization algorithm," *Bull. Electr. Eng. Informatics*, vol. 8, no. 1, pp. 30–38, 2019, doi: 10.11591/eei.v8i1.1442.
 - [36] S. S. Reddy, "Optimal placement of FACTS controllers for congestion management in the deregulated power system," *Int. J. Electr. Comput. Eng.*, vol. 8, no. 3, pp. 1336–1344, 2018, doi: 10.11591/ijece.v8i3.pp1336-1344.
 - [37] H. I. Hussein, G. A. Salman, and M. S. Hasan, "Phase measurement units based FACTS devices for the improvement of power systems networks controllability," *Int. J. Electr. Comput. Eng.*, vol. 8, no. 2, pp. 888–899, 2018, doi: 10.11591/ijece.v8i2.pp888-899.
 - [38] U. Kiliç and K. Ayan, "Optimal power flow solution of two-terminal HVDC systems using genetic algorithm," *Electr. Eng.*, vol. 96, no. 1, pp. 65–77, 2014.
 - [39] B. Saleh, J. Y. Lee, and R. Verayiah, "Voltage regulation and power loss reduction by integration of SVC in distribution networks via PSSE," *Int. J. Power Electron. Drive Syst.*, vol. 11, no. 3, p. 1579, 2020.
 - [40] B. Bhattacharyya and S. Raj, "Swarm intelligence based algorithms for reactive power planning with Flexible AC transmission system devices," *Int. J. Electr. Power Energy Syst.*, vol. 78, pp. 158–164, 2016.
 - [41] R. H. AL-Rubayi and L. G. Ibrahim, "Enhancement transient stability of power system using UPFC with M-PSO," *Indones. J. Electr. Eng. Comput. Sci.*, vol. 17, no. 1, pp. 61–69, 2019, doi: 10.11591/ijeecs.v17.i1.pp61-69.
 - [42] N. Cherkaoui, A. Belfqih, F. E. Mariami, J. Boukherouaa, and A. Berdai, "Optimal location and reactive power injection of wind farms and SVC's units using voltage indices and PSO," *Int. J. Electr. Comput. Eng.*, vol. 9, no. 5, pp. 3407–3414, 2019, doi: 10.11591/ijece.v9i5.pp3407-3414.
 - [43] S. C. B. Semlali, M. E. Riffi, and F. Chebihi, "Parallel hybrid chicken swarm optimization for solving the quadratic assignment problem," *Int. J. Electr. Comput. Eng.*, vol. 9, no. 3, pp. 2064–2074, 2019, doi: 10.11591/ijece.v9i3.pp2064-2074.
 - [44] L. Bougouff and A. Chaghi, "Optimal setting of DOC relay in distribution system in presence of D-FACTS," *Bull. Electr. Eng. Informatics*, vol. 10, no. 4, pp. 1811–1818, 2021, doi: 10.11591/EEI.V10I4.2809.
 - [45] A. M. Ghadban, G. A. Salman, and H. I. Hussein, "Assessment of voltage stability based on power transfer stability index using computational intelligence models," *Int. J. Electr. Comput. Eng.*, vol. 11, no. 4, pp. 2790–2797, 2021, doi: 10.11591/ijece.v11i4.pp2790-2797.
 - [46] G. A. Salman, H. G. Abood, and M. S. Ibrahim, "Improvement the voltage stability margin of Iraqi power system

- using the optimal values of FACTS devices,” *Int. J. Electr. Comput. Eng.*, vol. 11, no. 2, pp. 984–992, 2021, doi: 10.11591/ijece.v11i2.pp984-992.
- [47] M. M. H. Elroby, S. F. Mekhamer, H. E. A. Talaat, and M. A. Moustafa Hassan, “FACTS allocation considering loads uncertainty, steady state operation constraints, and dynamic operation constraints,” *Int. J. Electr. Comput. Eng.*, vol. 11, no. 2, pp. 945–955, 2021, doi: 10.11591/ijece.v11i2.pp945-955.
- [48] A. M. Hasan and S. M. Rafaat, “Optimized formation control of multi-agent system using PSO algorithm,” *Indones. J. Electr. Eng. Comput. Sci.*, vol. 20, no. 3, pp. 1591–1600, 2020, doi: 10.11591/ijeecs.v20.i3.pp1591-1600.
- [49] Y. Merzoug, B. Abdelkrim, and B. Larbi, “Distribution network reconfiguration for loss reduction using PSO method,” *Int. J. Electr. Comput. Eng.*, vol. 10, no. 5, pp. 5009–5015, 2020, doi: 10.11591/IJECE.V10I5.PP5009-5015.
- [50] B. Pati and S. B. Karajgi, “Optimized placement of multiple FACTS devices using PSO and CSA algorithms,” *Int. J. Electr. Comput. Eng.*, vol. 10, no. 4, pp. 3350–3357, 2020, doi: 10.11591/ijece.v10i4.pp3350-3357.
- [51] S. R. Salkuti, “Artificial fish swarm optimization algorithm for power system state estimation,” *Indones. J. Electr. Eng. Comput. Sci.*, vol. 18, no. 3, pp. 1130–1137, 2020, doi: 10.11591/ijeecs.v18.i3.pp1130-1137.
- [52] S. Khan and S. Bhowmick, “A novel power-flow model of multi-terminal VSC-HVDC systems,” *Electr. Power Syst. Res.*, vol. 133, pp. 219–227, 2016.
- [53] H. H. Goh *et al.*, “Types of circuit breaker and its application in substation protection,” *Indones. J. Electr. Eng. Comput. Sci.*, vol. 8, no. 1, pp. 213–220, 2017, doi: 10.11591/ijeecs.v8.i1.pp213-220.
- [54] Q. Chen, X. Dong, H. Li, T. Jin, J. Yi, and J. Tu, “A Method of Power Flow Calculation Considering New FACTS and HVDC,” in *Journal of Physics: Conference Series*, 2019, vol. 1187, no. 2, p. 22046.
- [55] B. S. Pali, S. Bhowmick, and N. Kumar, “Newton-Raphson power flow models of static VAR compensator,” in *2012 IEEE 5th India International Conference on Power Electronics (IICPE)*, 2012, pp. 1–5.
- [56] S. M. Yousuf and M. S. Subramaniyan, “HVDC and facts in power system,” *Int. J. Sci. Res.*, vol. 2, 2013.
- [57] A. M. Eltamaly, Y. Sayed, and A. N. A. Elghaffar, “A survey: HVDC System Operation and Fault Analysis,” *Int. J. Eng. Tome Novemb.*, 2017.
- [58] B. N. Patil and S. B. Karajgi, “Simultaneous placement of FACTS devices using cuckoo search algorithm,” *Int. J. Power Electron. Drive Syst.*, vol. 11, no. 3, p. 1344, 2020.
- [59] T. Shu *et al.*, “Probabilistic power flow analysis for hybrid HVAC and LCC-VSC HVDC system,” *IEEE Access*, vol. 7, pp. 142038–142052, 2019.
- [60] A. Raza, A. Shakeel, H. Tahzeeb, M. Jamil, and S. Gillani, “Economic analysis for HVDC transmission system in Pakistan,” *Int. J. Control Autom.*, vol. 10, no. 11, pp. 29–38, 2017.
- [61] I. M. Ginarsa, A. B. Muljono, I. M. A. Nnarthana, and S. Sultan, “Transient response improvement of direct current using supplementary control based on ANFIS for rectifier in HVDC,” *Int. J. Power Electron. Drive Syst.*, vol. 11, no. 4, p. 2107, 2020.
- [62] K. Alshammari, H. A. Alsiraji, and R. El Shatshat, “Optimal Power Flow in Multi-Terminal HVDC Systems,” in *2018 IEEE Electrical Power and Energy Conference (EPEC)*, 2018, pp. 1–6.
- [63] T. Nouredine and L. Djamel, “Load flow analysis using Newton-Raphson method in presence of distributed generation,” *Int. J. Power Electron. Drive Syst.*, vol. 12, no. 1, p. 489, 2021.
- [64] K.-H. Pho and V.-T. Nguyen, “Comparison of Newton-Raphson algorithm and Maxlik function,” *J. Adv. Eng. Comput.*, vol. 2, no. 4, pp. 281–292, 2018.
- [65] H. Abaali, E. Talbi, and R. Skouri, “Comparison of newton Raphson and gauss seidel methods for power flow analysis,” *World Acad. Sci. Eng. Technol. Int. J. Energy Power Eng.*, vol. 12, no. 9, pp. 627–633, 2018.
- [66] E. Karami, G. B. Gharehpetian, H. Mohammadpour, A. Khalilinia, and A. Bali, “Generalised representation of multi-terminal VSC-HVDC systems for AC–DC power flow studies,” *IET Energy Syst. Integr.*, vol. 2, no. 1, pp. 50–58, 2020.
- [67] A. M. Eltamaly, Y. Sayed, A.-H. M. El-Sayed, and A. N. A. Elghaffar, “Optimum power flow analysis by Newton raphson method, a case study,” *Ann Fac Eng Hunedoara*, vol. 16, no. 4, pp. 51–58s, 2018.
- [68] M. Zadehbagheri, R. Ildarabadi, and M. B. Nejad, “Review of dynamic voltage restorer application for compensation of voltage harmonics in power systems,” *Indones. J. Electr. Eng. Comput. Sci.*, vol. 5, no. 1, pp. 58–71, 2017, doi: 10.11591/ijeecs.v5.i1.pp58-71.
- [69] M. Zadehbagheri, R. Ildarabadi, M. B. Nejad, and T. Sutikno, “A new structure of dynamic voltage restorer based on asymmetrical Γ -source inverters to compensate voltage disturbances in power distribution networks,” *International Journal of Power Electronics and Drive Systems*, vol. 8, no. 1, pp. 344–359, 2017, doi: 10.11591/ijpeds.v8i1.pp344-359.
- [70] M. Zadehbagheri, R. Ildarabadi, and M. Baghaeinejad, “A novel method for modeling and simulation of asymmetrical impedance-source converters,” *Int. J. Eng. Trans. B Appl.*, vol. 31, no. 5, pp. 741–751, 2018, doi: 10.5829/ije.2018.31.05b.09.

BIOGRAPHIES OF AUTHORS

Abdolmajid Javadian, he was born in December 1989 in Yasuj, Iran. In 2013, he received his bachelor's degree in electrical engineering from Jundishapur University of Dezful, Iran. In 2015, he received a master's degree in electrical engineering from the Islamic Azad University, Yasouj Branch, Iran. He is currently studying for his doctorate at the Islamic Azad University of Yasouj Branch. His research interests include context FACTS and Power flow in power systems.



Mahmoud Zadehbagheri was born in Yasouj, Iran in October 1989. In 2003 he received his B.S. in Electrical Engineering from Kashan University and in 2008 he received his M.S. in Electrical Engineering from the Islamic Azad University, Najafabad Branch. He received the PhD degree in Electrical Engineering from Sabzevar Hakim Sabzevari University in 2017. He is with the faculty of the Electrical Engineering Department, Islamic Azad University of Yasouj. His research interests include the fields of power electronics, electrical machines and drives, FACTS devices and power quality.



Mohammad Javad Kiani was born in Yasouj, Iran in. In 2003 he received his B.S. in Electrical Engineering from K. N. Toosi University of Technology and in 2008 he received his M.S. in Electrical Engineering from the K. N. Toosi University of Technology. He received the PhD degree in Electrical Engineering from UTM University of Malaysia in 2017. He is with the faculty of the Electrical Engineering Department, Islamic Azad University of Yasouj. His research interests include the fields of Electronic and Power electronics.



Samad Nejatian was born in Yasouj, Iran, in 1981. He received his B.S. degree in Electrical Engineering from Zahedan University, Zahedan, Iran, in 2003; his M.S. degree in Electrical Engineering from the Ferdowsi University of Mashhad, Mashhad, Iran, in 2007; and his Ph.D. degree in Electrical Engineering from the UTM University of Malaysia, Skudai, Malaysia, in 2014. He is presently a faculty member and an Associate Professor in the Department of Electrical Engineering, Islamic Azad University, Yasouj, Iran. His current research interests include intelligent networks, control systems, reliability in power systems, and neural networks.



Tole Sutikno is a Lecturer in Electrical Engineering Department at the Ahmad Dahlan (UAD) University, Yogyakarta, Indonesia. He received his B.Eng., M.Eng. and Ph.D. degrees in Electrical Engineering from Diponegoro University, Universitas Gadjah Mada and Universiti Teknologi Malaysia, in 1999, 2004 and 2016, respectively. He has been an Associate Professor in UAD, Yogyakarta, Indonesia since 2008. He is currently an Editor-in-Chief of the TELKOMNIKA and the Head of the Embedded Systems and Power Electronics Research Group. His research interests include the field of digital design, industrial applications, industrial electronics, industrial informatics, power electronics, motor drives, renewable energy, FPGA applications, embedded system, artificial intelligence, intelligent control and digital library.