

## An assessment of the share contributions of distortion sources for various load parameters

Aleksandr Skamyin<sup>1</sup>, Yaroslav Shklyarskiy<sup>2</sup>, Iuliia Dobush<sup>2</sup>, Vasiliy Dobush<sup>2</sup>, Tole Sutikno<sup>3</sup>,  
Mohd Hatta Jopri<sup>4</sup>

<sup>1</sup>Department of Electric Power and Electromechanics, Saint Petersburg Mining University, Saint Petersburg, Russia

<sup>2</sup>Department of General Electrical Engineering, Saint-Petersburg Mining University, Saint Petersburg, Russia

<sup>3</sup>Department of Electrical Engineering, Universitas Ahmad Dahlan, Yogyakarta, Indonesia

<sup>4</sup>Faculty of Electrical and Electronic Engineering Technology, Universiti Teknikal Malaysia Melaka, Melaka, Malaysia

### Article Info

#### Article history:

Received Jan 13, 2022

Revised Mar 27, 2022

Accepted Apr 19, 2022

#### Keywords:

Harmonic distortion

Passive filter

Point of common coupling

Power quality

Share contribution

### ABSTRACT

The method for assessing the contributions of distortion sources based on measuring consumer currents and calculating their projections onto the supply current vector is considered in the paper. Determination of contributions is carried out on the basis of the developed model of an industrial enterprise in the food industry in MATLAB Simulink software. This study presents various cases of simulation, including variable parameters of linear and non-linear consumer load, changes in parameters of external distortion sources and passive harmonic filters. It is shown that the considered method gives correct results in the absence of external distortions in the electrical grid. The considered criteria for the share contributions make it possible to estimate the most efficient place for installing a passive filter in the absence of external distortions. An indicator for evaluating external distortions has also been developed based on calculating the projection of the harmonic system current onto the harmonic current of the shunt filter at the considered frequency.

*This is an open access article under the [CC BY-SA](https://creativecommons.org/licenses/by-sa/4.0/) license.*



### Corresponding Author:

Mohd Hatta Jopri

Faculty of Electrical and Electronic Engineering Technology, Universiti Teknikal Malaysia Melaka

Melaka, Malaysia

Email: hatta@utem.edu.my

## 1. INTRODUCTION

At present, the problem of improving the power quality is becoming widespread, since electrical equipment with semiconductor energy converters is being intensively introduced at any enterprise. Such equipment, in turn, significantly pollutes the electrical grid with harmonics, which can lead to a number of problems, including stoppage of technological lines and equipment failure [1]–[4]. This is typical not only for consumers with non-linear electrical loads, but also for consumers that do not distort the supply voltage. In this case, it is very important to determine the share contributions of distortion sources in the power quality indicators. A considerable number of developed methods are known for searching and identifying the contribution of consumers to the deterioration of the power quality [5]–[14]. At the same time, there are still no correct and approved methodologies and guidelines that allow identifying such a contribution at operating enterprises, and none of the developed methods is used to solve such problems in practice [15]. For example, the method for determining the consumers' contribution to voltage distortion, approved in 2002 in Russia, was canceled due to incorrect identification of distortion sources based on the method of switching on and off the load [10]. A large number of works are devoted to techniques based on the analysis of harmonic power flows and based on the determination of the phase shift angle between voltage and current at the harmonic

frequency [16]–[19]. A number of works provide a mathematical description of the processes confirming the inoperability of this method [20], [21].

The next fundamental stage in the development of methods for identifying distortion sources is the works based on the analysis of the Norton or Thevenin equivalent circuits [22]–[28]. When implementing this method, the equivalent conductivity of each consumer is determined, which is defined with significant assumptions and can have a significant error on the accuracy of the methods. A large number of works are devoted to improving methods for measuring the conductivity of the power supply system and consumers [29]–[34]. Invasive methods quite accurately estimate the parameters of the system and consumers based on the generation of current harmonics of a certain spectrum into the grid and the subsequent measurement of the harmonic voltage. However, the complexity of the source used to generate the signal into the grid significantly increases the cost of solving the problem.

The principle of some methods for identifying distortion sources is based on the calculation of one or another type of power flow. These methods include the calculation of active power flow, the reactive or inactive power flow, the distortion power flow. However, none of the methods provides accurate information on the percentage contribution of each distortion source to total distortions, but determines only the dominant source [35], [36].

There are also a number of methods, the essence of which is based on the analysis of the current and voltage vectors at the point of common coupling [37]–[42] where the division of responsibility for the generation of harmonic currents is determined by their projections onto the total current vector. In this case, a situation is possible when the current amplitude of the distorting consumer is greater than the current amplitude of the supply current vector of all consumers. Then the sum of the current harmonic projections will be more than 100%, which leads to an incorrect determination of the distortion sources contributions. Shklyarskiy *et al.* [43] developed a method based also on the analysis of current vectors and their projections onto the supply current vector, where the above disadvantages are additionally eliminated, which makes it possible to determine the presence of external distortions, provided that a passive harmonic filter is used. Thus, the purpose of this paper is to assess the share contributions of distortion sources based on the method developed by the authors using the example of modeling the power supply system of a food industry enterprise, which is confirmed for a number of different variations in load parameters.

## 2. RESEARCH METHOD

### 2.1. Method of distortion sources assessment

The method under study has been completely described in [30]. The main idea of the method is that the contribution of each consumer can be calculated as shown in (1).

$$K_D^{(h)} = \frac{I_{pr}^{(h)}}{I_0^{(h)}} \cdot 100\%, \tag{1}$$

Where  $I_0^{(h)}$  is the  $h$  harmonic current at the point of common coupling (PCC),  $I_{pr}^{(h)}$  is projection of the consumer's  $h$  harmonic current on  $I_0^{(h)}$ . It can be illustrated by the vector diagram shown in Figure 1. The case when two consumers are connected at the PCC is considered.




Figure 1. Relative positions of the currents' vectors

There are three different relative positions described in the vector diagram. For all options  $I_0^{(h)}$  remains the same but the first and the second consumers current vectors  $i_1^{(h)'} / i_2^{(h)'}$  are varied and marked as

$i_1^{(h)'}/i_1^{(h)''}/i_1^{(h)'''}$  and  $i_2^{(h)'}/i_2^{(h)''}/i_2^{(h)'''}$ . Consequently, the projections of the consumers'  $h$  harmonic currents on  $I_0^{(h)}$  are changed, namely, both their amplitudes and signs. Both projections  $I_{1pr}^{(h)''}$  and  $I_{2pr}^{(h)''}$  are positive that means that both of them are the  $h$  harmonic current sources. At the same time,  $I_{1pr}^{(h)'}$  is negative that indicates  $h$  harmonic current compensation by the first consumer. Similarly, negative  $I_{2pr}^{(h)'''}$  shows that the second consumer is the  $h$  harmonic current compensator.

**2.2. Case study**

To test the proposed method, the scheme of the power supply system of a food production enterprise with 630 and 1000 kVA input transformers, was considered. The calculations were carried out for one of the sections of a 0.4 kV switchgear, shown in Figure 2. The input of the main distribution panel (MDP), which, in turn, feeds five outgoing power panels, is powered from the said switchgear. The load of the power panels was presented in the form of equivalent loads by the types of electrical equipment, which makes it possible to clearly demonstrate the developed method. Thus, in this case, there are 5 outgoing panels, the load parameters of which are described in Table 1. To simulate the described power supply system in the MATLAB Simulink software environment, the parameters of the equivalent circuit for each element of the system were calculated. The equivalent circuit parameters are presented in Table 2.




Figure 2. The scheme under study

Table 1. The load's parameters

Panel's label	Load's type	Power (kVA)
LP	LEDs	40
VP	Ventilation with power converter	75
EP1	Process equipment (linear / non-linear load)	90 / 75
EP2	Process equipment (linear load)	37
CP	Compressors	110

Table 2. The parameters of the equivalent circuit

Elements of the scheme	Parameters and values
Energy system	U <sub>pss</sub> = 0.4 kV, X <sub>pss</sub> = 0.002 Ω
Transformer	S = 630 kVA, U <sub>HV</sub> = 10 kV, U <sub>LV</sub> = 0.4 kV, ΔP <sub>SC</sub> = 7.6 kW, U <sub>SC</sub> = 5.5. %
LP power line	l <sub>1</sub> = 150 m, R <sub>l1</sub> = 1.2 Ω/km, X <sub>l1</sub> = 0.0675 Ω/km
VP power line	l <sub>2</sub> = 100 m, R <sub>l2</sub> = 0.54 Ω/km, X <sub>l2</sub> = 0.0637 Ω/km
EP1 power line	l <sub>3</sub> = 100 m, R <sub>l3</sub> = 0.2 Ω/km, X <sub>l3</sub> = 0.0602 Ω/km
EP2 power line	l <sub>4</sub> = 150 m, R <sub>l4</sub> = 0.74 Ω/km, X <sub>l4</sub> = 0.0662 Ω/km
CP power line	l <sub>5</sub> = 100 m, R <sub>l5</sub> = 0.158 Ω/km, X <sub>l5</sub> = 0.0602 Ω/km
Harmonic filter	Q <sub>F</sub> = 25 k kvar, L <sub>F</sub> = 0.77 mH, C <sub>F</sub> = 530 μF, R <sub>F</sub> = 0.01 Ω

Lighting devices, being the load of the lighting panel (LP), are simulated according to the scheme presented in [2], where the authors consider computer models of semiconductor lighting devices. A model of type B LEDs, the current waveform of which coincides with the lighting devices at the enterprise and has the form shown in Figure 3, has been selected.

The load of the ventilation panel (VP) and the compressor panel (CP) is presented in the form of a standard induction motor unit with a frequency power converter (PC) with a scalar pulse-width modulation algorithm (PWM), the power consumption of which is controlled by changing the shaft torque. The non-linear load of the first process equipment panel (EP1) is also simulated by a standard induction motor unit with a thyristor power regulator (TPR). As in the case of scalar PWM, the load is controlled via changing the torque. The linear load of the EP1 and the second process equipment panel (EP2) is replaced by an induction motor with a squirrel cage rotor with a possibility of torque control. The harmonic filter is a shunt filter tuned to a specific frequency.




Figure 3. Lighting devices current waveform

### 3. RESULTS AND DISCUSSION

The power supply system (PSS), built on the MATLAB Simulink platform, was simulated for various parameters of the consumer load, filter connection points and external distortions. All calculations are conditionally divided into 3 blocks. These blocks provide the following modes: i) simulation without filter and external distortions, ii) simulation with a harmonic filter and without external distortions, and iii) simulation with external distortions.

#### 3.1. Block 1: Simulation without filter and external distortions

The single-line equivalent circuit for all experiments in block 1 looks the same, as shown in Figure 4. As can be seen from the scheme, the harmonic filter is not connected to the system, and the presence of external distortions from the grid is not assumed. Within the framework of each simulation, the load of one of the panels varied in relative units relative to the rated capacity of each panel, indicated in Table 1. The load parameters for each simulation are presented in Table 3.




Figure 4. PSS's and enterprise's equivalent circuit for block 1 simulations

Table 3. Loads' parameters for block 1 simulations

Simulation number	LP's load, p.u.	VP's load, p.u.	EP1's load (non-linear part), p.u.	EP2's load, p.u.	CP's load, p.u.
1	1	0.5÷1	1	1	1
2	1	1	0÷1	1	1
3	1	1	1	0÷1	1
4	1	1	1	1	0:0.5:1

It is assumed that the lighting load does not change, the fans are regulated in the range of 0.5÷1, the non-linear load of technological processes can change the power consumption in a wide range of 0÷1, and the compressors can either be switched off, or operate under the nominal mode or at half of this mode power. Simulation 1 was carried out with a change in the torque of the motor connected to the VP. The results of simulation 1 are presented in Table 4.

Analyzing the simulation results, it is worth noting that the EP2 linear load is characterized by a negative contribution of a small amplitude, slightly varying for different simulated modes from -5.55% to -5.65%. The contribution of the EP1 consumer, which includes both linear and non-linear loads, is characterized by a value close to the contribution of the linear load, since the non-linear consumer, being a part of it, generates such a 5th harmonic current that the projection of this current onto the current at the PCC is small. As a result, the total contribution of the non-linear and linear load of the consumer is closer to the contribution of the linear load. However, the change in this coefficient, depending on the VP loading, from -4.54% to -5.87% indicates that the non-linear load in the consumer of a mixed structure of the EP1 is still present. A similar situation with a small contribution of non-linear load can be observed with respect to the results of calculating the LP ratio. It is also seen that the contribution of the LP decreases from 2.72% to 2.30% and the contribution of the CP decreases from 83.51% to 77.18% with an increase in the load of another non-linear consumer. With an increase in the VP's load, the contribution of this consumer increased from 23.87% to 32.01%. As a result, the calculated coefficients fully reflect the contributions of consumers depending on the power consumption and, accordingly, the currents generated by them. During simulation 2, the load of the EP1 was changed. The results of simulation 2 are presented in Table 5.

Table 4. Simulation 1 results

Parameters	VP's load, p.u.					
	0.5	0.6	0.7	0.8	0.9	1
K <sub>D</sub> (LP), %	2.72	2.62	2.50	2.43	2.36	2.30
K <sub>D</sub> (VP), %	23.87	25.66	27.28	28.86	30.48	32.01
K <sub>D</sub> (EP1), %	-4.54	-4.85	-5.14	-5.40	-5.62	-5.84
K <sub>D</sub> (EP2), %	-5.55	-5.58	-5.58	-5.61	-5.63	-5.65
K <sub>D</sub> (CP), %	83.51	82.15	80.94	79.72	78.41	77.18
THD <sub>u</sub> (PCC), %	6.33	6.50	6.66	6.82	6.99	7.16
THD <sub>i</sub> (PCC), %	17.41	17.37	17.28	17.23	17.19	17.14
I <sup>(5)</sup> (PCC), A	78.87	81.15	83.37	85.64	87.96	90.25
I <sup>(5)</sup> (VP), A	23.34	25.81	28.14	30.44	32.77	35.02

Table 5. Simulation 2 results

Parameters	EP1's load, p.u.				
	0	0.25	0.5	0.75	1
K <sub>D</sub> (LP), %	0.88	1.28	1.64	1.98	2.30
K <sub>D</sub> (VP), %	37.44	36.13	34.79	33.42	32.01
K <sub>D</sub> (EP1), %	-12.92	-11.66	-10.03	-8.08	-5.84
K <sub>D</sub> (EP2), %	-6.04	-5.93	-5.83	-5.74	-5.65
K <sub>D</sub> (CP), %	80.65	80.18	79.43	78.42	77.18
THD <sub>u</sub> (PCC), %	7.01	7.04	7.08	7.12	7.16
THD <sub>i</sub> (PCC), %	18.19	17.75	17.45	17.25	17.14
I <sup>(5)</sup> (PCC), A	84.96	86.34	87.64	88.93	90.25
I <sup>(5)</sup> (EP1), A	11.03	11.44	14.68	19.33	24.54

Unlike the loads of the VP and the CP, the non-linear load of the EP1 is powered by a thyristor power regulator. During the simulation, it was revealed that the contribution of the EP1 increased from -12.92% to -5.84%. Negative values of contributions of a mixed structure consumer were analyzed in the previous simulation. The fact that the non-linear load of EP1 generates a 5th harmonic current, small relative to other consumers, is confirmed by the last line of the Table 5, where it can be seen that when the non-linear load is switched off, the current consumption is 11.03 A, obviously, caused by external sources of distortion, and at full loading the value of this current increases only to 24.54 A. As in the previous case, the contribution of the non-linear load of the EP2 changes slightly, while the contributions of the non-linear consumers of the VP and CP decrease. In this case, it can be noted that the proposed coefficient allows one to quantify the contributions of non-linear consumers, including consumers, which include both linear and non-linear loads. Within the framework of simulation 3, the load of the linear consumer of the EP2 was changed. The results of Simulation 3 are presented in Table 6.

According to the results of calculations, it can be seen that the operating mode of the linear load virtually does not affect the contributions of all consumers connected to the PCC. It can be observed that increasing the linear load decreases the THD<sub>i</sub> level, but this has virtually no effect on THD<sub>u</sub>. This effect is achieved by increasing the PCC current at the fundamental frequency with constant harmonic emissions from non-linear consumers. Simulation 4 was carried out with a change in the operating mode of the CP load. At

first, the CP's load was disconnected, then loaded by 0.5 of the rated power, after which it worked in the nominal mode. The results of Simulation 4 are presented in Table 7.

When the CP's load is off, the dominant source of the 5th harmonic distortions is the VP's load. When the compressors are connected at full power and by 0.5 of this value, the contributions are redistributed and the CP's load becomes the dominant source. As in previous simulations, the contribution of the load with an increase in capacity increases, while the contributions of other non-linear and mixed structure loads decrease. As a result, before connecting passive filters according to the proposed method, it is possible to assess the contributions of consumers with respect to current distortion at the PCC. It can be seen that the contribution directly depends on the amplitude and phase of the current generated directly by the consumer and is also determined by the current in the PCC, i.e. by the total impact of all consumers connected to the PCC. However, such calculations are acceptable only in case of insignificant distortions from the PSS. The case with a dominant source of distortion from the PSS is considered in block 3.

Table 6. Simulation 3 results

Parameters	EP2's load, p.u.				
	0	0.25	0.5	0.75	1
$K_D$ (LP), %	2.07	2.13	2.18	2.24	2.30
$K_D$ (VP), %	32.31	32.24	32.16	32.09	32.01
$K_D$ (EP1), %	-6.50	-6.34	-6.18	-6.01	-5.84
$K_D$ (EP2), %	-5.71	-5.70	-5.68	-5.67	-5.65
$K_D$ (CP), %	77.83	77.68	77.52	77.36	77.18
THDu (PCC), %	7.18	7.17	7.16	7.16	7.16
THDi (PCC), %	18.83	18.41	17.99	17.57	17.14
$I^{(5)}$ (PCC), A	89.81	89.90	90.01	90.12	90.25
$I^{(5)}$ (EP2), A	5.13	5.13	5.12	5.12	5.10

Table 7. Simulation 4 results

Parameters	CP's load, p.u.		
	0	0.5	1
$K_D$ (LP), %	2.81	2.80	2.30
$K_D$ (VP), %	105.53	41.65	32.01
$K_D$ (EP1), %	-3.20	-4.20	-5.84
$K_D$ (EP2), %	-5.14	-5.51	-5.65
$K_D$ (CP), %	0.00	65.25	77.18
THDu (PCC), %	4.25	5.86	7.16
THDi (PCC), %	16.49	17.32	17.14
$I^{(5)}$ (PCC), A	50.05	72.44	90.25
$I^{(5)}$ (CP), A	0.00	48.48	71.09

**3.2. Block 2: Simulation with a harmonic filter and without external distortions**

The single-line equivalent circuit for the simulation of block 2 is shown in Figure 5. It can be seen that the possibility of connecting the 5th harmonic filter to various nodes of the PSS, including the bus, as well as directly to consumers after the power lines, was simulated. During simulation 1 of block 2, a filter was connected to the bus. The contributions of consumers relative to the current at the PCC  $K_{D/PCC}$ , as well as the contributions of consumers and the power supply system relative to the filter current  $K_{D/F}$  were calculated. The calculation results are presented in Table 8. Due to the fact that after installing the filter, the value of the 5th harmonic current in the power supply system tends to zero, the calculated contributions of  $K_{D/PCC}$  are not informative, since the denominator of the expression for calculating the said value is too small. As for the contributions relative to the filter current, it is worth noting that the contribution of the power supply system is -1.99%, which fully reflects the source data, which do not provide for distortions from the power supply system. The linear load of the EP2, the non-linear load of the LP, and the mixed load of the EP1 are either not sources of the 5th harmonic current, or their amplitude is small. Therefore, they are characterized by negative contributions of small amplitude, while the contributions of other consumers reflect the distribution of responsibility for the generation of harmonic currents to the same extent as the results of simulations 1-4 of block 1 at the rated load of all consumers.




Figure 5. PSS's and enterprise's equivalent circuit for block 2 simulations

During simulation 2, the filter connection point was changed, and the contribution of the external system to the current distortion at the filter connection point was calculated taking into account all other loads connected to the bus. The calculation results are presented in Table 9. The contributions of the power supply system in relation to the filter current for each filter connection point were determined. When filter is connected to the PCC, a value of -1.99% can be observed, which indicates that the distortion sources are located on the consumer's side. When the filter is connected to the LP, the contribution of the power supply system is 121.62%, while in this case all consumers to which the filter is not connected are included in the power supply system. Similarly, it is worth noting that the impact of the external non-linear load on EP1 and EP2 is more than 100%. The connection of the filter to the PCC is preferable according to the Table 9 data. At the same time, this conclusion can be made based on the calculation of the contribution of  $K_{D/F}$ , since there is a direct relationship between this indicator and other power quality indicators at the PCC. The second efficient point in this case is the connection of the filter to the CP point with  $K_{D/F}=11.33\%$ .

Table 8. Simulation 1 results of block 2

Load	Parameters	
	$K_{D/PCC}, \%$	$K_{D/E}, \%$
LP	15.67	-5.42
VP	5.84	41.87
EP1	26.50	-12.83
EP2	-5.87	-0.06
CP	92.82	79.58
Filter	-12.93	---
PSS	---	-1.99

Table 9. Simulation 2 results of block 2

Filter connection point	Parameters			
	$K_{D/F}, \%$	THDu (PCC), %	THDi (PCC), %	$I^{(5)}$ (PCC), A
PCC	-1.99	4.75	12.50	42.13
LP	121.62	6.02	15.59	76.02
VP	31.01	5.13	13.42	50.94
EP1	116.96	5.02	13.26	49.78
EP2	101.04	5.70	15.18	70.78
CP	11.33	4.93	12.92	43.39

**3.3. Block 3: Simulation with external distortions**

The single-line equivalent circuit for the simulation of block 3 is similar to the circuit in Figure 5 with two corrections, the passive filter is connected to the PCC and there is a 5th harmonic voltage with 10% amplitude of the rated voltage. The simulation was carried out with a filter connected to the bus (Case 1 in Table 10) and without a filter (Case 2). Firstly, the contributions of consumers relative to the power supply system are not informative at this level of distortions, but the dominant source can still be identified. As in the simulation of block 2, when the filter is connected, the value of THDu (PCC) decreases from 10.55% to 6.29%. However, the value of THDi (PCC) increases from 21.09% to 22.47%, as does the 5th harmonic current at the PCC. This indicates that effective compensation of harmonics should be carried out in the nodes outside the considered enterprise. To determine the most effective filter connection point, it is possible to use the method of calculating harmonic current projections of the system onto the filter current. If the calculated contribution of  $K_{D/F} \approx 0$ , as in case when the filter is connected to the PCC in simulation 2 of block 2, then the compensation of harmonics is efficient. With an increase in  $K_{D/F}$ , the efficiency of harmonic compensation decreases.

Table 10. Simulation results of block 3

Load	Parameters					
	$K_{D/F}, \%$		THDu (PCC), %		THDi (PCC), %	
	1	2	1	2	1	2
PCC	44.44	---	6.29	10.55	22.47	21.09
LP	-2.28	-48.54				
VP	18.97	64.28				
EP1	-5.33	-61.28				
EP2	-0.09	26.03				
CP	45.41	119.51				

**4. CONCLUSION**

Thus, the conclusion that can be drawn from this research are: i) The direct dependence of the consumer's contribution on the power of non-linear loads with frequency converters and for LED lighting devices has been confirmed; ii) The constancy of the consumer's contribution with linear load, regardless of the load and operating modes of other consumers, connected to the same PCC, has been confirmed; iii) The considered criteria for the share contributions make it possible to estimate the most efficient place for installing a passive filter in the absence of external distortions; and iv) The efficiency of current distortion compensation decreases in the presence of distortions in power supply voltage. This can be characterized by

the introduced indicator  $K_{D/F}$  based on calculating harmonic current projections of the system onto the filter current filter, directly indicating which part of distortions will not be compensated for by the filter.

## ACKNOWLEDGEMENTS

This research was financially supported by the Russian Science Foundation Grant No. 21-79-10027, <https://rscf.ru/en/project/21-79-10027>.

## REFERENCES

- [1] D. Fallows, S. Nuzzo, A. Costabeber, and M. Galea, "Harmonic reduction methods for electrical generation: a review," *IJET Generation, Transmission & Distribution*, vol. 12, no. 13, pp. 3107-3113, 2018.
- [2] C. Yoon, H. Bai, R. N. Beres, X. Wang, C. L. Bak and F. Blaabjerg, "Harmonic Stability Assessment for Multiparalleled, Grid-Connected Inverters," *IEEE Transactions on Sustainable Energy*, vol. 7, no. 4, pp. 1388-1397, 2016, doi: 10.1109/TSTE.2016.2551737.
- [3] M. H. Jopri, M. R. Ab Ghaiii, A. R. Abdullah, M. Manap, T. Sutikno, and J. Too, "K-nearest neighbor and naïve bayes based diagnostic analytic of harmonic source identification," *Bulletin of Electrical Engineering and Informatics*, vol. 9, no. 6, pp. 2650-2657, 2020, doi: 10.11591/eei.v9i6.2685.
- [4] M. H. Jopri, A. R. Abdullah, T. Sutikno, M. Manap, M. R. A. Ghani, and M. R. Yusoff, "A Critical Review of Time-frequency Distribution Analysis for Detection and Classification of Harmonic Signal in Power Distribution System," *International Journal of Electrical and Computer Engineering*, vol. 8, no. 6, pp. 4603-4618, 2018, doi: 10.11591/ijece.v8i6.pp4603-4618.
- [5] B. N. Abramovich, "Uninterruptible power supply system for mining industry enterprises," *J. Min. Inst.*, vol. 229, no. 31, 2018, doi: 10.25515/PMI.2018.1.31.
- [6] A. A. Belsky, V. S. Dobush, and S. F. Haikal, "Operation of a Single-phase Autonomous Inverter as a Part of a Low-power Wind Complex," *J. Min. Inst.*, vol. 239, pp. 564-569, 2019, doi: 10.31897/PMI.2019.5.564.
- [7] J. M. Munoz-Guijosa, S. B. Kryltcov, and S. V. Solovev, "Application of an Active Rectifier used to mitigate currents distortion in 6-10 kV distribution grids," *J. Min. Inst.*, vol. 236, pp. 229-238, 2019, doi: 10.31897/PMI.2019.2.229.
- [8] J. G. Mayordomo, A. Carbonero, L. F. Beites, R. Asensi and W. Xu, "A Contribution Towards a General and Systematic Procedure for Modeling Line Commutated AC/DC Converters in the Harmonic Domain," *IEEE Transactions on Power Delivery*, vol. 24, no. 4, pp. 2415-2427, 2009, doi: 10.1109/TPWRD.2009.2027492.
- [9] Y. Li, Z. Deng, T. Wang, G. Zhao, and S. Zhou, "Coupled harmonic admittance identification based on least square estimation," *Energies*, vol. 11, no. 10, pp. 1-15, 2018, doi: 10.3390/en11102600.
- [10] E. J. Davis, A. E. Emanuel and D. J. Pileggi, "Harmonic pollution metering: theoretical considerations," *IEEE Transactions on Power Delivery*, vol. 15, no. 1, pp. 19-23, 2000, doi: 10.1109/61.847223.
- [11] X. Li, M. Chen, Y. Zheng, S. Cheng, and F. Li, "An Approach for Assessing Harmonic Emission Level Based on Robust Partial Least Squares Regression," *TELKOMNIKA Telecommunication Computing Electronics and Control*, vol. 12, no. 7, pp. 4981-4987, 2014, doi: 10.11591/telkomnika.v12i7.4584.
- [12] S. Kannan and J. Meyer, "Recent Developments in Harmonic Resonance Detection in Low Voltage Networks using Impedance Measurement Techniques," *8th International Conference on Power Systems (ICPS)*, 2019, pp. 1-6, doi: 10.1109/ICPS48983.2019.9067345.
- [13] R. Luhtala *et al.*, "Identification of three-phase grid impedance in the presence of parallel converters," *Energies*, vol. 12, no. 14, pp. 1-15, 2019, doi: 10.3390/en12142674.
- [14] T. Suntio *et al.*, "Impedance-based interactions in grid-tied three-phase inverters in renewable energy applications," *Energies*, vol. 12, no. 3, pp. 1-31, 2019, doi: 10.3390/en12030464.
- [15] Y. E. Shklyarskiy, D. D. Guerra, E. V. Iakovleva, and A. Rassölkin, "The influence of solar energy on the development of the mining industry in the Republic of Cuba," *J. Min. Inst.*, vol. 249, pp. 427-440, 2021.
- [16] S. Cheng *et al.*, "An open-circuit fault-diagnosis method for inverters based on phase current," *Transportation Safety and Environment*, vol. 2, no. 2, pp. 148-160, 2020, doi: 10.1093/TSE/TDAA008.
- [17] E. K. Robati and M. S. Sepasian, "Passive harmonic filter planning considering daily load variations and distribution system reconfiguration," *Electric Power Systems Research*, vol. 166, pp. 125-135, 2019, doi: 10.1016/j.epr.2018.09.019.
- [18] S. T. Jafrodi, M. Ghanbari, M. Mahmoudian, A. Najafi, E. MG Rodrigues, and E. Pouresmaeil, "A Novel Control Strategy to Active Power Filter with Load Voltage Support Considering Current Harmonic Compensation," *Applied Sciences*, vol. 10, no. 5, pp. 1-18, 2020, doi: 10.3390/app10051664.
- [19] Y. Zhukovskiy, P. Tsvetkov, A. Buldysko, Y. Malkova, A. Stoianova, and A. Koshenkova, "Scenario Modeling of Sustainable Development of Energy Supply in the Arctic," *Resources*, vol. 10, no. 12, pp. 1-25, 2021, doi: 10.3390/resources10120124.
- [20] W. Xu, X. Liu and Y. Liu, "An investigation on the validity of power-direction method for harmonic source determination," *IEEE Transactions on Power Delivery*, vol. 18, no. 1, pp. 214-219, 2003, doi: 10.1109/TPWRD.2002.803842.
- [21] F. Xu, H. Yang, J. Zhao, Z. Wang and Y. Liu, "Study on Constraints for Harmonic Source Determination Using Active Power Direction," *IEEE Transactions on Power Delivery*, vol. 33, no. 6, pp. 2683-2692, Dec. 2018, doi: 10.1109/TPWRD.2018.2828034.
- [22] E. Iakovleva, M. Belova, and A. Soares, "Allocation of potentially environmentally hazardous sections on pipelines," *Geosciences*, vol. 11, no. 1, pp. 1-11, 2021, doi: 10.3390/geosciences11010003.
- [23] N. Korolev, A. Kozyaruk, and V. Morenov, "Efficiency Increase of Energy Systems in Oil and Gas Industry by Evaluation of Electric Drive Lifecycle," *Energies*, vol. 14, no. 19, pp. 1-15, 2021, doi: 10.3390/en14196074.
- [24] X. Zhang, C. Li, D. Li and S. Jiang, "Study on Operation Parameter Characteristics of Induction Filter Distribution Transformer in Low-Voltage Distribution Network," *IEEE Access*, vol. 9, pp. 78764-78773, 2021, doi: 10.1109/ACCESS.2021.3083750.
- [25] J. C. L. da Silva, T. Ramos, and M. F. M. Júnior, "Modeling and Harmonic Impact Mitigation of Grid-Connected SCIG Driven by an Electromagnetic Frequency Regulator," *Energies*, vol. 14, no. 15, pp. 1-21, 2021, doi: 10.3390/en14154524.
- [26] D. Lumbreras, E. Gálvez, A. Collado, and J. Zaragoza, "Trends in power quality, harmonic mitigation and standards for light and heavy industries: A review," *Energies*, vol. 13, no. 21, pp. 1-24, 2020, doi: 10.3390/en13215792.
- [27] M. Tian, Y. Wang, and J. Li, "Comprehensive Harmonic Responsibility Calculation Based on Different Weighting Methods," *Energies*, vol. 12, no. 23, pp. 1-17, 2019, doi: 10.3390/en12234449.

- [28] Y.-O. Choi and J. Kim, "Output impedance control method of inverter-based distributed generators for autonomous microgrid," *Energies*, vol. 10, no. 7, pp. 1-15, 2017, doi: 10.3390/en10070904.
- [29] N. D. Senchilo and D. A. Ustinov, "Method for determining the optimal capacity of energy storage systems with a long-term forecast of power consumption," *Energies*, vol. 14, no. 21, pp. 1-25, 2021, doi: 10.3390/en14217098.
- [30] M. Y. Shabalov, Y. L. Zhukovskiy, A. D. Buldysko, B. Gil, and V. V. Starshaia, "The influence of technological changes in energy efficiency on the infrastructure deterioration in the energy sector," *Energy Reports*, vol. 7, pp. 2664-2680, 2021, doi: 10.1016/j.egyr.2021.05.001.
- [31] H. G. Beleiu, V. Maier, S. G. Pavel, I. Birou, C. S. Pică, and P. C. Dărab, "Harmonics consequences on drive systems with induction motor," *Applied Sciences*, vol. 10, no. 4, pp. 1-15, 2020, doi: 10.3390/app10041528.
- [32] C. K. Das *et al.*, "Optimal allocation of distributed energy storage systems to improve performance and power quality of distribution networks," *Applied Energy*, vol. 252, no. 15, pp. 113468, 2019, doi: 10.1016/j.apenergy.2019.113468.
- [33] O. Kalmbach, C. Dirscherl, and C. M. Hackl, "Discrete-time DC-link voltage and current control of a grid-connected inverter with LCL-filter and very small DC-link capacitance," *Energies*, vol. 13, no. 21, pp. 1-23, 2020.
- [34] V. Dovgun, S. Temerbaev, M. Chernyshov, V. Novikov, N. Boyarskaya, and E. Gracheva, "Distributed power quality conditioning system for three-phase four-wire low voltage networks," *Energies*, vol. 13, no. 18, pp. 1-19, 2020, doi: <https://doi.org/10.3390/en13184915>.
- [35] Y. V. Gulkov and D. A. Ustinov, "Electric power quality distortions influencing oil processing plant parameters and characteristics," *International Journal of Applied Engineering Research*, vol. 12, no. 9, pp. 2027-2030, 2017.
- [36] V. I. Alexandrov, A. V. Kopteva, and S. L. Serzan, "Effective parameters of gold-bearing ore hydrotransport for verninskaya processing factory," *Key Engineering Materials*, vol. 836, pp. 25-35, 2020, doi: 10.4028/www.scientific.net/KEM.836.25.
- [37] A. Patel, H. D. Mathur, and S. Bhanot, "An improved control method for unified power quality conditioner with unbalanced load," *International Journal of Electrical Power & Energy Systems*, vol. 100, pp. 129-138, 2018, doi: 10.1016/j.ijepes.2018.02.035.
- [38] A. M. dos Santos Alonso, D. I. Brandao, T. Caldognetto, F. P. Marafão, and P. Mattavelli, "A selective harmonic compensation and power control approach exploiting distributed electronic converters in microgrids," *International Journal of Electrical Power & Energy Systems*, vol. 115, p. 105452, 2020, doi: 10.1016/j.ijepes.2019.105452.
- [39] Z. M. Ali, F. Q. Alenezi, S. S. Kandil, and S. H. E. A. Aleem, "Practical considerations for reactive power sharing approaches among multiple-arm passive filters in non-sinusoidal power systems," *International Journal of Electrical Power & Energy Systems*, vol. 103, pp. 660-675, 2018, doi: 10.1016/j.ijepes.2018.06.044.
- [40] D. Bernet and M. Hiller, "Grid-connected medium-voltage converters with parallel voltage-source active filters," *IET Electric Power Applications*, vol. 13, no. 10, pp. 1507-1513, 2019.
- [41] D. Lumbreras, J. Zaragoza, J. Mon, E. Gálvez and A. Collado, "Efficiency analysis of wide band-gap semiconductors for two-level and three-level power converters," *IECON 2019 - 45th Annual Conference of the IEEE Industrial Electronics Society*, 2019, pp. 5126-5133, doi: 10.1109/IECON.2019.8926766.
- [42] N. H. H. and Abdullah, N. A., Abdullah, A. R., Zuri Sha'ameri, A., Shamsudin, N.H., Ahmad and M. H. Jopri, "Real-Time Power Quality Disturbances Detection and Classification System," *World Applied Sciences Journal*, vol. 32, no. 8, pp. 1637-1651, 2014, doi: 10.5829/idosi.wasj.2014.32.08.534.
- [43] Y. Shklyarskiy, I. Dobush, M. Jiménez Carrizosa, V. Dobush, and A. Skamyin, "Method for Evaluation of the Utility's and Consumers' Contribution to the Current and Voltage Distortions at the PCC," *Energies*, vol. 14, no. 24, pp. 1-21, 2021, doi: 10.3390/en14248416.

## BIOGRAPHIES OF AUTHORS



**Aleksandr Skamyin**     was born in Volkhov, Russia on 1986. He received his B.Eng and Ph.D. degree in electrical engineering from Saint-Petersburg Mining University (Russian Federation) in 2007 and 2011, respectively. From 2011 till 2015 he was the assistant in National Mineral Resources University (Mining University), Saint-Petersburg, Russian Federation. Since 2015, he is an associated professor in Saint-Petersburg Mining University (Russian Federation). His research interests include power quality, reactive power compensation in the presence of harmonics, regulation of power consumption mode. He can be contacted at email: [skamin\\_an@pers.spmi.ru](mailto:skamin_an@pers.spmi.ru).



**Yaroslav Shklyarskiy**     is a Lecturer in General Electrical Engineering Department at the Saint-Petersburg Mining University. He received a habilitated Doctor of Technical Sciences degree from the Krakow Mining and Metallurgical Academy in 1991. He received his Ph.D. degrees (doctoral dissertation) in Electrical Engineering from Saint-Petersburg Mining University in 2004. He has been lecturing at the Saint-Petersburg Mining University since 1977. From 2004 and till now he is academic supervisor of postgraduate students. He is currently an editorial board member of the *Electrical Power Quality and Utilization Journal* and *Journal of Mining Institute*. His research interests include the field of power quality, reactive power compensation, power flow control and regulation. He can be contacted at email: [shklyarskiy\\_YaE@pers.spmi.ru](mailto:shklyarskiy_YaE@pers.spmi.ru).



**Iuliia Dobush**    was born in Saint Petersburg, Russia in 1995. She received her Specialist Degree in Electrification and Automation of Mines from Saint Petersburg Mining University (Russia) in 2018. She has been a Ph.D. student in Electrical Engineering at Saint Petersburg Mining University (Russia) since 2018. Her research interests are electric power quality, harmonic distortion sources identification, non-linear loads equivalent circuits. She can be contacted at email: s185035@stud.spmi.ru.



**Vasiliy Dobush**    was born in Uchkulach, Uzbekistan in 1988. He received his B.Eng and Ph.D. degree in electrical engineering from Saint-Petersburg Mining University (Russian Federation) in 2010 and 2013, respectively. From 2013 till 2017 he was assistant in National Mineral resources University (Mining University), Saint-Petersburg, Russian Federation. Since 2017, he is associated professor in Saint-Petersburg Mining University (Russian Federation). His research interests include power quality, power harmonics, active harmonic filters, power converters. He can be contacted at email: dobush\_vs@pers.spmi.ru



**Tole Sutikno**    is a Lecturer in Electrical Engineering Department at the Universitas Ahmad Dahlan (UAD), Yogyakarta, Indonesia. He received his B.Eng., M.Eng. and Ph.D. degrees in Electrical Engineering from Universitas Diponegoro, Universitas Gadjah Mada and Universiti Teknologi Malaysia, in 1999, 2004 and 2016, respectively. He is an Associate Professor in UAD, Yogyakarta, Indonesia since 2008. He is currently an Editor-in-Chief of the TELKOMNIKA since 2005, and the Head of the Embedded Systems and Power Electronics Research Group since 2016. His research interests include the field of industrial applications, industrial electronics, industrial informatics, power electronics, motor drives, renewable energy, FPGA applications, embedded system, image processing, artificial intelligence, intelligent control, digital design and digital library. He can be contacted at email: tole@ee.uad.ac.id.



**Mohd Hatta Jopri**    received his B.Eng. from Universiti Teknologi Malaysia (UTM), Msc. in Electrical Power Engineering from Rheinisch-Westfälische Technische Hochschule Aachen (RWTH), Germany, and Ph.D. degree from Universiti Teknikal Malaysia Melaka (UTeM), respectively. Since 2005, he is an academia and research staff at UTeM. He is registered with Malaysia Board of Technologist (MBOT), Board of Engineers Malaysia (BEM) and a member of International Association of Engineers (IAENG). His research interests include power electronics and drive, power quality analysis, signal processing, machine learning and data science. He can be contacted at email: hatta@utem.edu.my.